


LOOX 350mA LED 4003 DOWNLIGHTS

The extremely small and flat design of these recessed Loox downlights makes it easy to integrate them in any furniture design.

350mA SYSTEM



Loox 350mA LED 4003 square downlight



- > For recess mounting, press-fit in Ø 28 mm hole
- > Current: 350mA. Wattage: 1W
- > With 2.0 m lead with 350mA connector
- > Plastic
- > Order qty: Multiples of 3 pcs

| | | |
|-------------------------|------------|----------------|
| Output: | 3000 K | 6000 K |
| Light colour: | Warm white | Daylight white |
| Wattage (W): | 1 | 1 |
| Energy efficiency: | A+ | A+ |
| Number of diodes: | 1 | 1 |
| Light output (Lm): | 68 | 92 |
| Efficacy (Lm/W): | 68 | 94 |
| Colour Rendering Index: | 85 | 85 |

| Distance | 130° | 3000 K | 6000 K |
|----------|------|--------|--------|
| 250 mm | | 248 Lx | 346 Lx |
| 500 mm | | 62 Lx | 86 Lx |
| 750 mm | | 28 Lx | 38 Lx |
| 1000 mm | | 15 Lx | 21 Lx |



| | | |
|-----------------|------------|------------|
| Finish | 3000 K | 6000 K |
| Silver coloured | 833.78.040 | 833.78.041 |

YOU ALSO NEED:



DRIVER
Page 165



SWITCH
Pages 167-170

OPTIONAL ACCESSORIES
Pages 166, 171